

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes****9.1 Local Transport Interface Groups**

Ten Interface Groups are provided for terminating the Local Transport at the customer's premises. Each Interface Group provides a specified premises interface code (e.g., two-wire, four-wire, DS1, etc.). At the option of the customer and where transmission facilities permit, the individual transmission path between the customer's premises and the first point of switching may be provided with optional features as set forth in 6.3.1 preceding.

As a result of the customer's access order and the type of Telephone Company transport facilities serving the customer's premises, the need for signaling conversions or two-wire to four-wire conversions, or the need to terminate digital or high frequency facilities in channel bank equipment may require that Telephone Company equipment be placed at the customer's premises. For example, if a voice frequency interface is ordered by the customer and the Telephone Company facilities serving the customer's premises are digital, then Telephone Company channel bank equipment must be placed at the customer's premises in order to provide the voice frequency interface ordered by the customer.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.1 Local Transport Interface Groups (Cont'd)**

Interface Group 1 is provided with Type C Transmission Specifications, and Interface Groups 2 through 10 are provided with Type A or B Transmission Specifications, depending on the Feature Group or Basic Serving Arrangement and whether the Access Service is routed directly or through an access tandem. All Interface Groups are provided with Data Transmission Parameters.

Only certain premises interfaces are available at the customer's premises. The premises interfaces codes associated with the Interface Groups may vary among Feature Groups and Basic Serving Arrangements. The various premises interfaces codes which are available with the Interface Groups or Basic Serving Arrangements, and the Feature Groups with which they may be used, are set forth in 9.1.11 following.

For each of the ten Interface Groups described following, the transmission path between the point of termination at the customer's premises and the first point of switching may be comprised of any form or configuration of plant and equipment capable of and typically used in the telecommunications industry for the transmission of voice and associated telephone signals within the frequency bandwidth of 300 to 3000 Hz.

**9.1.1 Interface Group 1**

Interface Group 1 provides a two-wire voice frequency transmission path at the point of termination at the customer's premises. Interface Group 1 is not provided in association with FGC, FGD, BSA-C and BSA-D when the first point of switching is an access tandem. In addition, Interface Group 1 is not provided in association with FGB, FGC, FGD, BSA-B, BSA-C or BSA-D when the first point of switching can only provide four-wire terminations.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.1 Local Transport Interface Groups (Cont'd)****9.1.1 Interface Group 1 ((Cont'd)**

The interface is provided with loop supervisory signaling. When the interface is associated with FGA or BSA-A, such signaling will be loop start or ground start signaling. When the interface is associated with FGB, FGC, FGD, BSA-B, BSA-C or BSA-D, such signaling will be reverse battery signaling. When FGB, FGC, FGD, BSA-B, BSA-C or BSA-D access service is associated with a two-way calling interface, E&M signaling shall be used.

**9.1.2 Interface Group 2**

Interface Group 2 provides four-wire voice frequency transmission at the point of termination at the customer's premises. The interface is provided with loop supervisory signaling. When the interface is associated with FGA or BSA-A, such signaling will be loop start or ground start signaling. When the interface is associated with FGB, FGC, FGD, BSA-B, BSA-C or BSA-D such signaling, except for two-way calling which is E&M signaling, will be reverse battery signaling.

**9.1.3 Interface Group 3**

Interface group 3 provides group level analog transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals between the frequencies of 60 to 180 kHz, with the capability to channelize up to 12 voice frequency transmission paths. Certain frequencies within the bandwidth of the Interface Group are reserved for Telephone Company use, e.g., pilot and carrier group alarm tones. Before the first point of switching, the Telephone Company will provide multiplex equipment to derive 12 transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz.

The interface is provided with SF supervisory signaling for each individual transmission channel.

As of December 30, 1993, Interface Group 3 is available to existing customers only.

(This page filed under Transmittal No. 26.)

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.1 Local Transport Interface Groups (Cont'd)****9.1.4 Interface Group 4**

Interface group 4 provides supergroup level analog transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals between the frequencies of 312 to 552 kHz, with the capability to channelize up to 60 voice frequency transmission paths. Certain frequencies within the bandwidth of the Interface Group are reserved for Telephone Company use, e.g., pilot and carrier group alarm tones. Before the first point of switching, the Telephone Company will provide multiplex and channel bank equipment to derive 60 transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz.

The interface is provided with SF supervisory signaling for each individual transmission channel.

As of December 30, 1993, Interface Group 4 is available to existing customers only.

**9.1.5 Interface Group 5**

Interface Group 5 provides mastergroup level analog transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals between the frequencies of 564 to 3084 kHz, with the capability to channelize up to 600 voice frequency transmission paths. Certain frequencies within the bandwidth of the Interface Group are reserved for Telephone Company use, e.g., pilot and carrier group alarm tones. Before the first point of switching, the Telephone Company will provide multiplex and channel bank equipment to derive 600 transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz.

The interface is provided with SF supervisory signaling for each individual transmission channel.

As of December 30, 1993, Interface Group 5 is available to existing customers only.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.1 Local Transport Interface Groups (Cont'd)****9.1.6 Interface Group 6**

Interface Group 6 provides DS1 level digital transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals at a nominal 1.544 Mbps, with the capability to channelize up to 24 voice frequency transmission paths. Before the first point of switching, when analog switching utilizing analog terminations is provided, the Telephone Company will provide multiplex and channel bank equipment to derive 24 transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz. When digital switching or analog switching with digital carrier terminations is provided, the Telephone Company will provide, at the first point of switching, a DS1 signal in D3/D4 format.

The interface is provided with bit stream supervisory signaling for each individual transmission channel.

**9.1.7 Interface Group 7**

Interface Group 7 provides DS1C level digital transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals at a nominal 3.152 Mbps, with the capability to channelize up to 48 voice frequency transmission paths. Before the first point of switching, when analog switching utilizing analog terminations is provided, the Telephone Company will provide multiplex and channel bank equipment to derive up to 48 voice frequency transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz. When digital switching or analog switching with digital carrier terminations is provided, the Telephone Company will provide, at the first point of switching, DS1 signals in D3/D4 format.

The interface is provided with bit stream supervisory signaling for each individual transmission channel.

As of December 30, 1993, Interface Group 7 is available to existing customers only.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.1. Local Transport Interface Groups (Cont'd)****9.1.8 Interface Group 8**

Interface Group 8 provides DS2 level digital transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals at a nominal 6.312 Mbps, with the capability to channelize up to 96 voice frequency transmission paths. Before the first point of switching, when analog switching utilizing analog terminations is provided, the Telephone Company will provide multiplex and channel bank equipment in its office to derive up to 96 transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz. When digital switching, or analog switching with digital carrier terminations is provided, the Telephone Company will provide, at the first point of switching, DS1 signals in D3/D4 format.

The interface is provided with bit stream supervisory signaling for each individual transmission channel.

Interface Group 8 is provided on an Individual Case Basis.

**9.1.9 Interface Group 9**

Interface Group 9 provides DS3 level digital transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals at a nominal 44.736 Mbps, with the capability to channelize up to 672 voice frequency transmission paths. Before the first point of switching, when analog switching utilizing analog terminations is provided, the Telephone Company will provide multiplex and channel bank equipment to derive up to 672 transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz. When digital switching, or analog switching with digital carrier terminations is provided, the Telephone Company will provide, at the first point of switching, DS1 signals in D3/D4 format.

The interface is provided with bit stream supervisory signaling for each individual transmission channel.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.1 Local Transport Interface Groups (Cont'd)****9.1.10 Interface Group 10**

Interface Group 10 provides DS4 level digital transmission at the point of termination at the customer's premises. The interface is capable of transmitting electrical signals at a nominal 274.176 Mbps, with the capability to channelize up to 4032 voice frequency transmission paths. Before the first point of switching, when analog switching utilizing analog terminations is provided, the Telephone Company will provide multiplex and channel bank equipment to derive up to 4032 transmission paths with a frequency bandwidth of approximately 300 to 3000 Hz. When digital switching or analog switching with digital carrier terminations is provided, the Telephone Company will provide, at the first point of switching, DS1 signals in D3/D4 format.

The interface is provided with bit stream supervisory signaling for each individual transmission channel.

Interface Group 10 is provided on an Individual Case Basis.

**9.1.11 Available Premises Interface Codes**

Following is a matrix showing which premises interface codes are available for each Interface Group as a function of the Telephone Company switch supervisory signaling and Feature Group. For explanations of these codes, see the Glossary of Channel Interface Codes in 9.3.1 following.

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes** (Cont'd)**9.1 Local Transport Interface Groups** (Cont'd)**9.1.11 Available Premises Interface Codes** (Cont'd)

<u>Interface Group</u>	<u>Telephone Company Switch Supervisory Signaling</u>	<u>Premises Interface Code</u>	<u>Feature Group</u>			
			<u>A</u>	<u>B</u>	<u>C</u>	<u>D</u>
1	LO	2LS2	X			
	LO	2LS3	X			
	GO	2GS2	X			
	GO	2GS3	X			
	LO, GO	2DX3	X			
	LO, GO	4EA3-E	X			
	LO, GO	4EA3-M	X			
	LO, GO	6EB3-E	X			
	LO, GO	6EB3-M	X			
	RV, EA, EB, EC	2DX3		X	X	X
	RV, EA, EB, EC	4EA3-E		X	X	X
	RV, EA, EB, EC	4EA3-M		X	X	X
	RV, EA, EB, EC	6EB3-E		X	X	X
	RV, EA, EB, EC	6EB3-M		X	X	X
	EA, EB, EC	6EC3			X	X
	RV	2RV3-O		X	X	X
	RV	2RV3-T		X	X	X
2	LO, GO	4SF2	X			
	LO, GO	4SF3	X			
	LO	4LS2	X			
	LO	4LS3	X			
	LO	6LS2	X			
	GO	4GS2	X			
	GO	4GS3	X			
	GO	6GS2	X			
	LO, GO	4DX2	X			
	LO, GO	4DX3	X			
	LO, GO	6EA2-E	X			
	LO, GO	6EA2-M	X			
	LO, GO	8EB2-E	X			
	LO, GO	8EB2-M	X			
	LO, GO	6EX2-B	X			

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes** (Cont'd)**9.1 Local Transport Interface Groups** (Cont'd)**9.1.11 Available Premises Interface Codes** (Cont'd)

<u>Interface Group</u>	<u>Telephone Company Switch Supervisory Signaling</u>	<u>Premises Interface Code</u>	<u>Feature Group</u>			
			<u>A</u>	<u>B</u>	<u>C</u>	<u>D</u>
2(Cont'd)	RV, EA, EB, EC	4SF2	X	X	X	
	RV, EA, EB, EC	4SF3	X			
	RV, EA, EB, EC	4DX2	X	X	X	
	RV, EA, EB, EC	4DX3	X	X	X	
	RV, EA, EB, EC	6DX2		X		
	RV, EA, EB, EC	6EA2-E	X	X	X	
	RV, EA, EB, EC	6EA2-M	X	X	X	
	RV, EA, EB, EC	8EB2-E	X	X	X	
	RV, EA, EB, EC	8EB2-M	X	X	X	
	EA, EB, EC	8EC2-M			X	X
	RV	4RV2-O	X	X	X	
	RV	4RV2-T	X	X	X	
	RV	4RV3-O	X	X		
	RV	4RV3-T	X	X		
3	LO, GO	4AH5-B	X			
	RV, EA, EB, EC	4AH5-B		X	X	X
4	LO, GO	4AH6-C	X			
	RV, EA, EB, EC	4AH6-C		X	X	X
5	LO, GO	4AH6-D	X			
	RV, EA, EB, EC	4AH6-D		X	X	X
6	LO, GO	4DS9-15	X			
	LO, GO	4DS9-15L	X			
	RV, EA, EB, EC	4DS9-15		X	X	X
	RV, EA, EB, EC	4DS9-15L		X	X	X
7	LO, GO	4DS9-31	X			
	RV, EA, EB, EC	4DS9-32		X	X	X
	LO, GO	4DS9-31L	X			
	RV, EA, EB, EC	4DS9-31L		X	X	X

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes** (Cont'd)**9.1 Local Transport Interface Groups** (Cont'd)**9.1.11 Available Premises Interface Codes** (Cont'd)

<u>Interface Group</u>	<u>Telephone Company Switch Supervisory Signaling</u>	<u>Premises Interface Code</u>	<u>Feature Group</u>			
			<u>A</u>	<u>B</u>	<u>C</u>	<u>D</u>
8	LO, GO	4DSO-63	X			
	LO, GO	4DSO-63L	X			
	RV, EA, EB, EC	4DSO-63		X	X	X
	RV, EA, EB, EC	4DSO-63L		X	X	X
9	LO, GO	4DS6-44	X			
	LO, GO	4DS6-44L	X			
	RV, EA, EB, EC	4DS6-44		X	X	X
	RV, EA, EB, EC	4DS6-44L		X	X	X
10	LO, GO	4DS6-27	X			
	LO, GO	4DS6-27L	X			
	RV, EA, EB, EC	4DS6-27		X	X	X
	RV, EA, EB, EC	4DS6-27L		X	X	X

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications, and Channel Codes (Cont'd)****9.2 Transmission Specifications for Switched Access Service**

The Telephone Company will maintain existing transmission specifications on functioning service configurations installed prior to the effective date of this tariff except that service configurations having performance specifications exceeding the standards listed in this provision will be maintained at performance levels specified in this tariff.

The transmission specifications contained in this Section are immediate action limits. Acceptance limits are set forth in Technical Reference GR-334-CORE, Issue 1. This Technical Reference also provides the basis for determining Switched Access Service maintenance limits.

**9.2.1 Standard Transmission Specifications**

Following are descriptions of the three Standard Transmission Specifications available with Switched Access Services. The specific applications in terms of the Switched Access Arrangements and Interface Groups with which the Switched Access Arrangement Standard Transmission Specifications are provided are set forth in 6.2 preceding.

**(A) Type A Transmission Specifications**

Type A Transmission Specifications is provided with the following parameters:

**(1) Loss Deviation**

The maximum Loss Deviation of the 1004 Hz loss relative to the Expected Measured Loss (EML) is  $\pm 2.0$  dB.

(x) GR-334-CORE, Issue 1, replaces TR-NPL-000334 in its entirety.

---

ACCESS SERVICE

---

**9. Interface Groups, Transmission Specifications, and Channel Codes** (Cont'd)**9.2 Transmission Specifications for Switched Access Service** (Cont'd)**9.2.1 Standard Transmission Specifications** (Cont'd)**(A) Type A Transmission Specifications** (Cont'd)**(2) Attenuation Distortion**

The maximum Attenuation Distortion in the 404 to 2804 Hz frequency band relative to the loss 1004 Hz is -1.0 dB to +3.0 dB.

**(3) C-Message Noise**

The maximum C-Message Noise for the transmission path at the route miles listed is less than or equal to:

<u>Route Miles</u>	<u>C-Message Noise</u>
less than 50	32 dBmCO
51 to 100	34 dBmCO
101 to 200	37 dBmCO
201 to 400	40 dBmCO
401 to 1000	42 dBmCO

**(4) C-Notch Noise**

The maximum C-Notch Noise, utilizing a -16 dBmO holding tone, is less than or equal to 45 dBmCO.

**(5) Echo Control**

Echo Control, identified as Equal Level Echo Path Loss, and expressed as Echo Return Loss and Singing Return Loss, is dependent on the routing, i.e., whether the service is routed directly from the customer's point of termination (POT) to the end office or via an access tandem. It is equal to or greater than the following:

---

ACCESS SERVICE

---

9. Interface Groups, Transmission Specifications, and Channel Codes (Cont'd)9.2 Transmission Specifications for Switched Access Service (Cont'd)9.2.1 Standard Transmission Specifications (Cont'd)(A) Type A Transmission Specifications (Cont'd)(5) Echo Control (Cont'd)

	<u>Echo Return Loss</u>	<u>Singing Return Loss</u>
POT to Access Tandem	21 dB	14 dB
POT to End Office		
- Direct	N/A	N/A
- Via Access Tandem	16 dB	11 dB

(6) Standard Return Loss

Standard Return Loss expressed as Echo Return Loss and Singing Return Loss on two-wire ports of a four-wire point of termination shall be equal to or greater than:

<u>Echo Return Loss</u>	<u>Singing Return Loss</u>
5 dB	2.5 dB

(B) Type B Transmission Specifications

Type B Transmission Specifications is provided with the following parameters:

(1) Loss Deviation

The maximum Loss Deviation of the 1004 Hz loss relative to the Expected Measured Loss (EML) is  $\pm 2.5$  dB.

(2) Attenuation Distortion

The maximum Attenuation Distortion is the 404 to 2804 Hz frequency band relative to loss at 1004 Hz is -2.0 dB to +4.0 dB.

---

**ACCESS SERVICE**


---

**9. Interface Groups, Transmission Specifications, and Channel Codes (Cont'd)****9.2 Transmission Specifications for Switched Access Service (Cont'd)****9.2.1 Standard Transmission Specifications (Cont'd)****(B) Type B Transmission Specifications (Cont'd)****(3) C-Message Noise**

The maximum C-Message Noise for the transmission path at the route miles listed is less than or equal to:

<u>Route Miles</u>	<u>C-Message Noise*</u>	
	<u>Type B1</u>	<u>Type B2</u>
less than 5	32 dBrnCO	35 dBrnCO
51 to 100	33 dBrnCO	37 dBrnCO
101 to 200	35 dBrnCO	40 dBrnCO
201 to 400	37 dBrnCO	43 dBrnCO
401 to 1000	39 dBrnCO	45 dBrnCO

**(4) C-Notch Noise**

The maximum C-Notch Noise, utilizing a -16 dBmO holding tone is less than or equal to 47 dBrnCO.

**(5) Echo Control**

Echo Control, identified as Impedance Balance for FGA, FGB, BSA-A and BSA-B and Equal Level Echo Path Loss for FGC, FGD, BSA-C and BSA-D and expressed as Echo Return Loss (ERL) and Singing Return Loss (SRL), is dependent on the routing, i.e., whether the service is routed directly from the customer's point of termination (POT) to the end office or via an access tandem. The ERL and SRL also differ by Switched Access Service, type of termination, and type of transmission path. They are greater than or equal to the following:

\* For FGC, FGD, BSA-C and BSA-D only Type B2 will be provided. For FGA, FGB, BSA-A and BSA-B, Type B1 or B2 will be provided as set forth in Technical Reference GR-334-CORE, Issue 1.

## ACCESS SERVICE

9. Interface Groups, Transmission Specifications, and Channel Codes (Cont'd)9.2 Transmission Specifications for Switched Access Service (Cont'd)9.2.1 Standard Transmission Specifications (Cont'd)(B) Type B Transmission Specifications (Cont'd)(5) Echo Control (Cont'd)

	<u>Echo Return Loss</u>	<u>Singing Return Loss</u>
POT to Access Tandem		
- Terminated in		
4-Wire trunk	21 dB	14 dB
POT to End Office		
- Terminated in		
2-Wire trunk	16 dB	11 dB
POT to End Office		
- Direct	16 dB	11 dB
-Via Access Tandem		
▪ For FGB and BSA-B access	8 dB	4 dB
▪ For FGC and BSA-C access		
(Effective		
4-Wire trans-		
mission path		
at end office)	16 dB	11 dB
▪ For FGC and BSA-C access		
(Effective		
2-Wire trans-		
mission path		
at end office)	13 dB	6 dB

(6) Standard Return Loss

Standard Return Loss, expressed as Echo Return Loss and Singing return Loss, on two-wire ports of a four-wire point of termination shall be equal to or greater than:

<u>Echo Return Loss</u>	<u>Singing Return Loss</u>
5 dB	2.5 dB

---

ACCESS SERVICE

---

**9. Interface Groups, Transmission Specifications, and Channel Codes** (Cont'd)**9.2 Transmission Specifications for Switched Access Service** (Cont'd)**9.2.1 Standard Transmission Specifications** (Cont'd)**(C) Type C Transmission Specification**

Type C Transmission Specifications is provided with the following parameters:

**(1) Loss Deviation**

The maximum Loss Deviation of the 1004 Hz loss relative to the Expected Measured Loss (EML) is  $\pm 3.0$  dB.

**(2) Attenuation Distortion**

The maximum Attenuation Distortion in the 404 to 2804 Hz frequency band relative to loss at 1004 Hz is -2.0 dB to +5.5 dB.

**(3) C-Message Noise**

The maximum C-Message Noise for the transmission path at the route miles listed is less than or equal to:

<u>Route Miles</u>	<u>C-Message Noise*</u>	
	<u>Type B1</u>	<u>Type B2</u>
less than 50	32 dBrnCO	38 dBrnCO
51 to 100	33 dBrnCO	39 dBrnCO
101 to 200	35 dBrnCO	41 dBrnCO
201 to 400	37 dBrnCO	43 dBrnCO
401 to 1000	39 dBrnCO	45 dBrnCO

**(4) C-Notch Noise**

The maximum C-Notch Noise, utilizing a -16 dBmO holding tone is less than or equal to 47 dBrnCO.

\* For FGC, FGD, BSA-C and BSA-D only Type C2 will be provided. For FGA, FGB, BSA-A and BSA-B, Type C1 or C2 will be provided set forth in Technical Reference GR-334-CORE, Issue 1.

---

**ACCESS SERVICE**


---

**9. Interface Groups, Transmission Specifications, and Channel Codes (Cont'd)****9.2 Transmission Specifications for Switched Access Service (Cont'd)****9.2.1 Standard Transmission Specifications (Cont'd)****(C) Type C Transmission Specifications (Cont'd)****(5) Echo Control**

Echo Control, identified as Return Loss and expressed as Echo Return Loss and Singing Return Loss is dependent on the routing, i.e., whether the service is routed directly from the customer's point of termination (POT) to the end office or via an access tandem. It is equal to or greater than the following:

	<u>Echo Return Loss</u>	<u>Singing Return Loss</u>
POT to Access Tandem	13 dB	6 dB
POT to End Office		
- Direct	13 dB	6 dB
- Via Access Tandem	8 dB	4 dB
(for FGB and BSA-B only)		

---

ACCESS SERVICE

---

**9. Interface Groups, Transmission Specifications, and Channel Codes** (Cont'd)**9.2 Transmission Specifications for Switched Access Service** (Cont'd)**9.2.2 Data Transmission Parameters**

Two types of Data Transmission Parameters, i.e., Type DA and Type DB, are provided for the Switched Access Service arrangements. The specific applications in terms of the Feature Groups with which they are provided are set forth in 6.2 preceding. In addition, the Combined Access Service Arrangement is provided with Data Transmission Parameters. Following are descriptions of each parameter.

**(A) Data Transmission Parameters Type DA****(1) Signal to C-Notched Noise Ratio**

The Signal to C-Notched Noise Ratio is equal to or greater than 33 dB.

**(2) Envelope Delay Distortion**

The maximum envelope Delay Distortion for the frequency bands and route miles specified is:

<u>604 to 2804 Hz</u>	
less than 30 route miles	500 microseconds
equal to or greater than 30 route miles	900 microseconds

<u>1004 to 2404 Hz</u>	
less than 50 route miles	200 microseconds
equal to or greater than 50 route miles	400 microseconds

**(3) Impulse Noise Counts**

The Impulse Noise Counts exceeding a 65 dBmCO threshold in 15 minutes is no more than 15 counts.

**(4) Intermodulation Distortion**

The Second Order (R2) and Third Order (R3) Intermodulation Distortion products are equal to or greater than:

Second Order (R2)	33 dB
Third Order (R3)	37 dB

---

**ACCESS SERVICE**

---

**9.        Interface Groups, Transmission Specifications, and Channel Codes** (Cont'd)**9.2       Transmission Specifications for Switched Access Service** (Cont'd)**9.2.2     Data Transmission Parameters** (Cont'd)**(A)       Data Transmission Parameters Type DA** (Cont'd)**(5)       Phase Jitter**

The Phase Jitter over the 4-300 Hz frequency band is less than or equal to 5° peak-to-peak.

**(6)       Frequency Shift**

The maximum Frequency Shift does not exceed -2 to +2 Hz.

---

ACCESS SERVICE

---

**9. Interface Groups, Transmission Specifications, and Channel Codes** (Cont'd)**9.2 Transmission Specifications for Switched Access Service** (Cont'd)**9.2.2 Data Transmission Parameters** (Cont'd)**(B) Data Transmission Parameters Type DB****(1) Signal to C-Notched Noise Ratio**

The signal to C-Notched Noise Ratio is equal to or greater than 30 dB.

**(2) Envelope Delay Distortion**

The maximum Envelope Delay Distortion for the frequency bands and route miles specified is:

<u>604 to 2804 Hz</u>	
less than 50 route miles	800 microseconds
equal to or greater than 50 route miles	1000 microseconds

<u>1004 to 2404 Hz</u>	
less than 50 route miles	320 microseconds
equal to or greater than 50 route miles	500 microseconds

**(3) Impulse Noise Counts**

The Impulse Noise Counts exceeding a 67 dBmCO threshold in 15 minutes is no more than 15 counts.

**(4) Intermodulation Distortion**

The Second Order (R2) and Third Order (R3) Intermodulation Distortion products are equal to or greater than:

Second Order (R2)	31 dB
Third Order (R3)	34 dB

**(5) Phase Jitter**

The Phase Jitter over the 4-300 Hz frequency band is less than or equal to 7° peak-to-peak.

**(6) Frequency Shift**

The maximum frequency Shift does not exceed -2 to +2 Hz.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes**

This section explains the Channel Interface codes and Network Channel codes that the customer must specify when ordering Special Access Service. Included is an example which explains the specific characters of the code, a glossary of Channel Interface codes, impedance levels, Network Channel codes and compatible Channel Interfaces.

Example: If the customer specifies a NT Network Channel Code and a 2DS8-3 Channel Interface at the customer's premises, the following is being requested:

NT = Metallic Circuit with a Predefined Technical  
Specification Package (1)  
2 = Number of physical wires at customer premises  
DS = Facility interface for direct current or voltage  
8 = Variable impedance level  
3 = Metallic facilities (DC continuity) for direct  
current/low frequency control signals or slow speed  
data (30 baud)

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.1 Glossary of Channel Interface Codes and Options**

<u>Code</u>	<u>Option</u>	<u>Definition</u>
AB -		accepts 20 Hz ringing signal at customer's point of termination
AC -		accepts 20 Hz ringing signal at customer's end user's point of termination
AH -		analog high capacity interface
-	B	60 kHz to 108 kHz (12 channels)
-	C	312 kHz to 552 kHz (60 channels)
-	D	564 kHz to 3084 kHz (600 channels)
CT -		Centrex Tie Trunk Termination
DA -		data stream in VF frequency band at customer's end user's point of termination
DB -		data stream in VF frequency band at customer's point of termination
-	10	VF for TG1 and TG2
-	43	VF for 43 Telegraph Carrier type signals, TG1 and TG2 DC -direct current or voltage
-	1	monitoring interface with series RC combination (McCulloh format)
-	2	Telephone Company energized alarm channel
-	3	Metallic facilities (DC continuity) for direct current/low frequency control signals or slow speed data (30 baud)
DD -		DATAPHONE Select-A-Station (and TABS) interface at customer's point of termination
DE -		DATAPHONE Select-A-Station (and TABS) interface at the customer's end user's point of termination
DS -		digital hierarchy interface
-	15	1.544 Mbps (DS1) format per PUB 41451 plus D4
-	15E	8-bit PCM encoded in one 64 kbps of the DS1 signal
-	15F	8-bit PCM encoded in two 64 kbps of the DS1 signal
-	15G	8-bit PCM encoded in three 64 kbps of the DS1 signal
-	15H	14/11-bit PCM encoded in six 64 kbps of the DS1 signal
-	15J	1.544 Mbps format per PUB 41451

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.1 Glossary of Channel Interface Codes and Options (Cont'd)**

<u>Code</u>	<u>Option</u>	<u>Definition</u>
DS (Cont'd)		
-	15K	1.544 Mbps format per PUB 41451 plus extended framing format
-	15L	1.544 Mbps (DS1) with SF signaling
-	27	274.176 Mbps (DS4)
-	27L	274.176 Mbps (DS4) with SF signaling
-	31	3.152 Mbps (DS1C)
-	31L	3.152 Mbps (DS1C) with SF signaling
-	44	44.736 Mbps (DS3)
-	44L	44.736 Mbps (DS3) with SF signaling
-	63	6.312 Mbps (DS2)
-	63L	6.312 Mbps (DS2) with SF signaling
DU -		digital access interface
-	19	19.2 kbps
-	24	2.4 kbps
-	48	4.8 kbps
-	56	56.0 kbps
-	64	64 kbps
-	96	9.6 kbps
-	A	1.544 Mbps format per PUB 41451
-	B	1.544 Mbps format per PUB 41451 plus D4
-	C	1.544 Mbps format per PUB 41451 plus extended framing format
DX -		duplex signaling interface at customer's point of termination
DY -		duplex signaling interface at customer's end user's point of termination
EA -	E	type I E&M Lead Signaling. Customer at POT or customer's end user at POT originates on E Lead.
EA -	M	Type I E&M Lead Signaling. Customer at POT or customer's end user at POT originates on M Lead.
EB -	E	Type II E&M Lead Signaling. Customer at POT or customer's end user at POT originates on E Lead.
EB -	M	Type II E&M Lead Signaling. Customer at POT or customer's end user at POT originates on M Lead.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.1 Glossary of Channel Interface Codes and Options (Cont'd)**

<u>Code</u>	<u>Option</u>	<u>Definition</u>
EC -		Type III E&M signaling at customer POT
EX -	A	tandem channel unit signaling for loop start or ground start and customer supplies open end (dial tone, etc.) functions.
EX -	B	tandem channel unit signaling for loop start or ground start and customer supplies closed end (dial pulsing, etc.) functions.
GO -		ground start loop signaling - open end function by customer or customer's end user.
GS -		ground start loop signaling - closed end function by customer or customer's end user
IA -		E.I.A. (25 pin RS-232)
LA -		end user loop start loop signaling - Type A OPS registered port open end
LB -		end user loop start loop signaling - Type B OPS registered port open end
LC -		end user loop start loop signaling - Type C OPS registered port open end
LO -		loop start loop signaling - open end function by customer or customer's end user
LR -		20 Hz automatic ringdown interface at customer with Telephone Company provided PLAR
LS -		loop start loop signaling - closed end function by customer or customer's end user
NO -		no signaling interface, transmission only
PG -		program transmission - no dc signaling
-	1	nominal frequency from 50 to 15000 Hz
-	3	nominal frequency from 200 to 3500 Hz
-	5	nominal frequency from 100 to 5000 Hz
-	8	nominal frequency from 50 to 8000 Hz

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.1 Glossary of Channel Interface Codes and Options (Cont'd)**

<u>Code</u>	<u>Option</u>	<u>Definition</u>
PR		protective relaying*
RV -	O	reverse battery signaling, one way operation, originate by customer
	-T	reverse battery signaling, one way operation, terminate function by customer or customer's end user
SF -		single frequency signaling with VF band at either customer POT or customer's end user POT
TF -		telephotograph interface
TT -		telegraph/teletypewriter interface at either customer POT or customer's end user POT
	-2	20.0 milliamperes
	-3	3.0 milliamperes
	-6	62.5 milliamperes
TV -		television interface
	-1	combined (duplexed) video and one audio signal
	-2	combined (duplexed) video and two audio signals
	-5	video plus one (or two) audio 5 kHz signal(s) or one (or two) two wire

\* Available only for the transmission of audio tone protective relaying signals used in the protection of electric power systems during fault conditions.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.1 Glossary of Channel Interface Codes and Options (Cont'd)**

<u>Code</u>	<u>Option</u>	<u>Definition</u>
-	15	video plus one (or two) audio 15 kHz signal(s)
WA -		wideband bandwidth interface at customer's end user POT
-	1	limited bandwidth
-	2	nominal passband from 29000 to 44000 Hz
WB -		wideband data interface at customer POT
-	18S	18.75 kbps, synchronous
-	19A	up to 19.2 kbps asynchronous
-	19S	19.2 kbps synchronous
-	23A	up to 230.4 kbps, asynchronous
-	23S	230.4 kbps, synchronous
-	40S	40.8 kbps, synchronous
-	50A	up to 50.0 kbps, asynchronous
-	50S	50.0 kbps synchronous
WC -		wideband data interface at customer's end user
-	18	POT 18.75 kbps, synchronous
-	19	for 12-wire interface: 19.2 kbps, synchronous
		for 10-wire interface: up to 19.2 kbps,
	23	asynchronous up to 230.4 kbps, asynchronous
-	23S	230.4 kbps, synchronous
-	40	40.8 kbps, synchronous
-	50	for 12-wire interface: 50.0 kbps, synchronous
		for 10-wire interface: up to 50.0 kbps, asyn-
WD -		chronous wideband bandwidth interface at customer POT
-	1	nominal passband from 300 to 18000 Hz
-	2	nominal passband from 28000 to 44000 Hz
-	3	nominal passband from 29000 to 44000 Hz

---

ACCESS SERVICE

---

9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)9.3 Channel Interface and Network Channel Codes (Cont'd)9.3.2 Impedance

The nominal reference impedance with which the channel will be terminated for the purpose of evaluating transmission performance:

<u>Value (ohms)</u>	<u>Code(s)</u>
110	0
150	1
600	2
900	3+
135	5
75	6
124	7
Variable	8
100	9

+ For those interface codes with a 4-wire transmission path at the customer's POT, rather than a standard 900 ohm impedance the code (3) denotes a customer provided transmission equipment termination. Such terminations were provided to customers in accordance with the F.C.C. Docket No. 20099 Settlement Agreement.

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.3 Digital Hierarchy Channel Interface Codes (4DS)**

Customers selecting the multiplexed four-wire DSX-1 or higher facility interface option at the customer designated premises will be requested to provide subsequent system and channel assignment data. The various digital bit rates in the digital hierarchy employ the channel interface code 4DS8, 4DS9, 4DS0 or 4DS6 plus the speed options indicated below:

<u>Interface Code and Speed Option</u>	<u>Nominal Bit Rate (Mbps)</u>	<u>Digital Hierarchy Level</u>
4DS8-15	1.544	DS1
4DS9-31	3.152	DS1C
4DS0-63	6.312	DS2
4DS6-44	44.736	DS3
4DS6-27	274.176	DS4

---

**ACCESS SERVICE**


---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.4 Service Designator/Network Channel Code Conversion Table**

The purpose of this table is to show the relationship between the service designator codes (e.g. VGC, MT2, etc.) and the network channel codes that are used for various administrative purposes.

<u>Service Designator Code</u>	<u>Network Channel Code</u>
MTC	MQ
MT1	NT
MT2	NU
MT3	NV
TGC	NQ
TG1	NW
TG2	NY
VGC	LQ
VG1	LB
VG2	LC
VG3	LD
VG4	LE
VG5	LF
VG6	LG
VG7	LH
VG8	LJ
VG9	LK
VG10	LN
VG11	LP
VG12	LR
APC	PQ
AP1	PE
AP2	PF
AP3	PJ
AP4	PK
TVC	TQ
TV1	TV
TV2	TW

---

**ACCESS SERVICE**

---

**9. Interface Groups, Transmission Specifications and Channel Codes** (Cont'd)**9.3 Channel Interface and Network Channel Codes** (Cont'd)**9.3.4 Service Designator/Network Channel Code Conversion Table** (Cont'd)

<u>Service Designator Code</u>	<u>Network Channel Code</u>
WA1	WJ
WA1T	WQ
WA2	WL
WA2A	WR
WA3	WN
WA4	WP
WD1	WB
WD2	WE
WD3	WF
DA1	XA
DA2	XB
DA3	XG
DA4	XH
HCO	HS
HC1	HC
HC1C	HD
HC2	HE
HC3	HF
HC4	HG

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces**

The following tables show the channel interface codes (CIs) which are compatible:

**(A) Metallic**Compatible CIs

4AH5-B	2DC8-1
4AH5-B	24C8-2
4AH6-C	2DC8-1
4AH6-C	2DC8-2
4AH6-D	2DC8-1

Compatible CIs

4AH6-D	2DC8-2
2DC8-1	2DC8-2
2DC8-3	2DC8-3
4DS9-*	2DC8-1
4DS9-*	2DC8-2

**(B) Telegraph Grade**Compatible CIs

4AH5-B	10IA8
4AH5-B	2TT2-2
4AH5-B	4TT2-2
4AH5-B	2TT2-6
4AH5-B	4TT2-6
4AH6-C	10IA8
4AH6-C	2TT2-2
4AH6-C	4TT2-2
4AH6-C	2TT2-6
4AH6-C	4TT2-6
4AH6-D	10IA8
4AH6-D	2TT2-2
4AH6-D	4TT2-2
4AH6-D	2TT2-6

Compatible CIs

4AH6-D	4TT2-6
2DB2-10	10IA8
2DB2-10	2TT2-2
2DB2-10	4TT2-2
2DB2-43+	10IA8
2DB2-43+	2TT2-2
2DB2-43+	2TT2-6
2DB2-43+	4TT2-2
4DB2-10	10IA8
4DB2-10	2TT2-2
4DB2-10	4TT2-2
4DB2-43+	10IA8
4DB2-43+	2TT2-6

Compatible CIs

4DB2-43+	4TT2-2
4DS9-*	10IA8
4DS9-*	2TT2-2
4DS9-*	4TT2-2
4DS9-*	2TT2-6
4DS9-*	4TT2-6
2TT2-2	2TT2-2
2TT2-3	2TT2-2
2TT2-3	4TT2-2
2TT2-6	2TT2-6
2TT2-6	4TT2-2
4TT2-2	4TT2-2
4TT2-6	2TT2-6

\* See 7.5.3 preceding for explanation.

+ Supplemental Channel Assignment information required.

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade**Compatible CIsCompatible CIsCompatible CIs

4AB2 4AB2

4AB2 4AC2

4AB3 4AC2

4AB2 2AC2

4AB3 2AC2

2AB2 2AC2

2AB3 2AC2

4AB2 4SF2

4AB3 4SF2

4AH6-D 4AC2

4AH6-D 2AC2

4AH6-C 4AC2

4AH6-C 2AC2

4AH5-B 4AC2

4AH5-B 2AC2

4AH6-D 2CT3

4AH6-C 2CT3

4AH5-B 2CT3

4AH6-D 6DA2

4AH6-D 4DA2

4AH6-D 2DA2

4AH6-C 6DA2

4AH6-C 4DA2

4AH6-C 2DA2

4AH5-B 6DA2

4AH5-B 4DA2

4AH5-B 2DA2

4AH6-D 4DE2

4AH6-C 4DE2

4AH5-B 4DE2

4AH6-D 2DE2

4AH6-C 2DE2

4AH5-B 2DE2

4AH6-D 4DX3

4AH6-C 4DX3

4AH5-B 4DX3

4AH6-D 4DX2

4AH6-C 4DX2

4AH5-B 4DX2

4AH6-D 9DY2

4AH6-D 9DY3

4AH6-D 6DY2

4AH6-D 6DY3

4AH6-D 4DY2

4AH6-D 2DY2

4AH6-C 9DY2

4AHG-C 9DY3

4AH6-C 6DY2

4AH6-C 6DY3

4AH6-C 4DY2

4AH6-C 2DY2

4AH5-B 9DY2

4AH5-B 9DY3

4AH5-B 6DY2

4AH5-B 6DY3

4AH5-B 4DY2

4AH5-B 2DY2

4AH6-D 9EA2

4AH6-D 9EA3

4AH6-D 6EA2-E

4AH6-D 6EA2-M

4AH6-D 4EA2-E

4AH6-D 4EA2-M

4AH6-C 9EA2

4AJ7-C 9EA3

4AH6-C 6EA2-E

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**

<u>Compatible CIs</u>		<u>Compatible CIs</u>		<u>Compatible CIs</u>	
4AH6-C	6EA2-M	4AH6-D	6GS2	4AH6-D	2LO2
4AH6-C	4EA2-E	4AH6-D	4GS2	4AH6-C	2LO3
4AH6-C	4EA2-M	4AH6-D	2GS3	4AH6-C	2LO2
4AH5-B	9EA2	4AH6-D	2GS2	4AH5-B	2LO3
4AH5-B	9EA3	4AH6-C	6GS2	4AH5-B	2LO2
4AH5-B	6EA2-E	4AH6-C	4GS2		
4AH5-B	6EA2-M	4AH6-C	2GS3	4AH6-B	4LR2
4AH5-B	4EA2-E	4AH6-C	2GS2	4AH6-D	2LR2
4AH5-B	4EA2-M	4AH5-B	6GS2	4AH6-C	4LR2
		4AH5-B	4GS2	4AH6-C	2LR2
4AH6-D	8EB2-E	4AH5-B	2GS3	4AH5-B	4LR2
4AH6-D	8EB2-M	4AH5-B	2GS2	4AH5-B	2LR2
4AH6-D	6EB2-E				
4AH6-D	6EB2-M	4AH6-D	2LA2	4AH6-D	6LS2
4AH6-C	8EB2-E	4AH6-C	2LA2	4AH6-D	4LS2
4AH6-C	8EB2-M	4AH5-B	2LA2	4AH6-D	2LS2
4AH6-C	6EB2-E			4AH6-D	2LS3
4AH6-C	6EB2-M	4AH6-D	2LB2	4AH6-C	6LS2
4AH5-B	8EB2-E	4AHG-C	2LB2	4AH6-C	4LS2
4AH5-B	8EB2-M	4AH5-B	2LB2	4AH6-C	2LS2
4AH5-B	6EB2-E			4AH6-C	2LS3
4AH5-B	6EB2-M	4AH6-D	2LC2	4AH5-B	6LS2
		4AH6-C	2LC2	4AH5-B	4LS2
		4AH5-B	2LC2	4AH5-B	2LS2
4AH6-D	2GO2				
4AH6-D	2GO3				
4AH6-C	2GO2				
4AH6-C	2GO2			4AH5-B	2LS3
4AH5-B	2GO2	4AH6-D	2LO3		
4AH5-B	2GO3				

## ACCESS SERVICE

9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)9.3 Channel Interface and Network Channel Codes (Cont'd)9.3.5 Compatible Channel Interfaces (Cont'd)(C) Voice Grade (Cont'd)

<u>Compatible CIs</u>		<u>Compatible CIs</u>		<u>Compatible CIs</u>	
4AH6-D	4NO2	4AH6-D	4TF2	2CT3	8EB2-E
4AH6-D	2NO2	4AJ7-D	2TF2	2CT3	8EB2-M
4AH6-C	4NO2	4AH6-C	4TF2		
4AH6-C	2NO2	4AH6-C	2TF2	2CT3	6482-E
4AH5-B	4NO2	4AH5-B	4TF2	2CT3	6EB2-M
4AH5-B	2NO2	4AH5-B	2TF2		
				2CT3	6EB3-E
				4DS9-*	
			2CT3	2CT3	8EC2
		2CT3	6DX2		
		2CT3	4DX2	2CT3	4SF2
		2CTS	4DX3	2CT3	4SF3
4AH6-D	4PR2	2CT3	9DY3	6DA2	6DA2
4AH6-D	2PR2	2CT3	6DY3	6DA2	4DA2
4AH6-C	4PR2	2CT3	9DT2	4DA2	4DA2
4AH6-C	2PR2	2CT3	6DY2		
4AH5-B	4PR2	2CT3	4DY3	4DB2	6DA2
4AH5-B	2PR2	2CT3	2DY2	4DB2	4DA2
				4DB2	2DA2
4AH6-D	4RV2-T	2CT3	9EA3	2DB3	2DA2
4AH6-D	2RV2-T	2CT3	9EA2	2DB2	2DA2
4AH6-C	4RV2-T	2CT3	6EA2-E	4DB2	4DB2
4AH6-C	2RV2-T	2CT3	6EA2-M	4DB2	4NO2
4AH5-B	4TV2-T	2CT3	4EA2-E	4DB2	2NO2
4AH5-B	2RV2-T	2CT3	4EA2-M	2DB2	2NO2
4AH6-D	4SF2			4DB2	4PR2
4AH6-C	4SF2			4DB2	2PR2
4AH5-B	4SF2			2DB2	2PR2
4AH6-D	4SF3				
4AH6-C	4SF3				
4AH5-B	4SF3				

\* See 9.3.3 preceding for explanation.

---

**ACCESS SERVICE**


---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**Compatible CIs

4DD3 4DE2  
4DD3 2DE2

4DS8-\* 4AC2  
4DS8-\* 2AC2

4DS8-\* 6DA2  
4DS8-\* 4DA2  
4DS8-\* 2DA2

4DS8-\* 4DE2  
4DS8-\* EDE2

4DS8-\* 4DX3  
4DS8-\* 4DX2

Compatible CIs

4DS8-\* 9DY3  
4DS8-\* 9DY2  
4DS8-\* 6DY3  
4DS8-\* 6DY2  
4DS8-\* 4DY2  
4DS8-\* 2DY2

4DS8-\* 9EA2  
4DS8-\* 9EA3  
4DS8-\* 6EA2-E  
4DS8-\* 6EA2-M  
4DS8-\* 4EA2-E  
4DS8-\* 4EA2-E

\* See 9.3.3 preceding for explanation.

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**Compatible CIsCompatible CIsCompatible CIs

4DS8-*	8EB2-E	4DS8-*	4NO2	4DX3	9DY2
4DS8-*	8EB2-M	4DS8-*	2NO2	4DX2	6DY3
4DS8-*	6EB2-E			4DX3	6DY3
4DS8-*	6EB2-M	4DS8-*	4PR2	4DX2	6DY2
		4DS8-*	2PR2	4DX3	6DY2
4DS8-*	2GO2			4DX2	4DY2
4DS8-*	2GO3	4DS8-*	4RV2-T	4DX3	4DY2
4DS8-*	6GS2	4DS8-*	2RV2-T	4DX2	2DY2
4DS8-*	4GS2			4DX3	2DY2
4DS8-*	2GS2	4DS8-*	4SF2		
4DS8-*	2GS3	4DS8-*	4SF3	6DX2	9EA3
				6DX2	9EA2
4DS8-*	2LA2	4DS8-*	4TF2	6DX2	6EA2-E
		4DS8-*	2TF2	6DX2	6EA2-M
4DS8-*	2LB2			6DX2	4EA2-E
		4DX2	4DX2	6DX2	4EA2-M
8DS8-*	2LC2	4DX3	4DX2	4DX2	9EA2
		4DX3	4DX3	4DX3	9EA2
4DS8-*	2LO2			4DX2	9EA3
4DS8-*	2LO3	6DX2	9DY3	4DX3	9EA3
		6DX2	9DY2	4DX2	6EA2-E
4DS8-*	4LR2	6DX2	6DY3	4DX3	6EA2-E
4DS8-*	2LR2	6DX2	6DY2	4DX2	6EA2-M
		6DX2	4DY2	4DX3	6EA2-M
4DS8-*	6LS2	6DX2	2DY2	4DX2	4EA2-E
4DS8-*	4LS2	4DX2	9DY3	4DX3	4EA2-E
4DS8-*	2LS2	4DX3	9DY3	4DX2	4EA2-M
4DS8-*	2LS3	4DX2	9DY2	4DX3	4EA2-M

\*

See 9.3.3 preceding for explanation.

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**

<u>Compatible CIs</u>		<u>Compatible CIs</u>		<u>Compatible CIs</u>	
6DX2	8EB2-E	4DX2	6LS2	9DY2	6DY3
6DX2	8EB2-M	4DX3	6LS2	9DY3	4DY2
6DX2	6EB2-E	4DX3	4LS2	9DY2	4DY2
6DX2	6EB2-M	4DX2	4LS2	9DY2	2DY2
4DX2	8EB2-E	4DX3	2LS3	9DY3	2DY2
4DX2	8EB2-M	4DX2	2LS3	6DY3	6DY3
4DX3	8EB2-E	4DX3	2LS2	6DY3	6DY2
4DX3	8EB2-M	4DX2	2LS2	6DY2	6DY2
4DX2	6EB2-E	2DX3	2LS2	6DY3	4DY2
4DX2	6EB2-M	2DX3	2LS3	6DY3	2DY2
4DX3	6EB2-E			6DY2	4DY2
4DX3	6EB2-M	4DX3	4RV2-T	6DY2	2DY2
		4DX2	4RV2-T	4DY2	2DY2
4DX2	2LA2	4DX3	2RV2-T	4DY2	4DY2
4DX3	2LA2	4DX2	2RV2-T		
2DX3	2LA2			6EA2-E	4AC2
		6DX2	4SF2	6EA2-M	4AC2
4DX2	2LB2	4DX2	4SF2	6EA2-E	2AC2
4DX3	2LB2	4DX3	4SF2	6EA2-M	2AC2
2DX3	2LB2	4DX2	4SF3		
		4DX3	4SF3	9EA2	9DY3
4DX2	2LC2			9EA2	9DY2
4DX3	2LC2	9DY3	9DY3	9EA2	6DY3
2DX3	2LC2	9DY3	9DY2	9EA2	6DY2
		9DY2	9DY2	9EA2	4DY2
4DX2	2LO3	9DY3	6DY3	9EA2	2DY2
4DX3	2LO3	9DY3	6DY2	9EA3	9DY3
2DX3	2LO3	9DY2	6DY2		

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**Compatible CIsCompatible CIsCompatible CIs

9EA3	9DY2	4EA2-M	9DY2	4EA3-E	9EA2
9EA3	6DY3	4EA2-M	6DY3	4EA3-E	9EA3
9EA3	6DY2	4EA2-M	6DY2	4EA2-M	4EA2-M
9EA3	4DY2	4EA2-M	4DY2		
9EA3	2DY2	4EA2-M	2DY2	9EA2	8EB2-E
6EA2-E	9DY3			9EA2	8EB2-M
6EA2-E	9DY2	9EA2	9EA2	9EA2	6EB2-E
6EA2-E	6DY3	9EA2	9EA3	9EA2	6EB2-M
6EA2-E	6DY2	9EA2	6EA2-E	9EA3	8EB2-E
6EA2-E	4DY2	9EA2	6EA2-M	9EA3	8EB2-M
6EA2-E	2DY2	9EA2	4EA2-E	9EA3	6EB2-E
6EA2-M	9DY3	9EA2	4EA2-M	9EA3	6EB2-M
6EA2-M	9DY2	9EA3	9EA3	6EA2-E	8EB2-E
6EA2-M	6DY3	9EA3	6EA2-E	6EA2-E	8EB2-M
6EA2-M	6DY2	9EA3	6EA2-M	6EA2-E	6EB2-E
6EA2-M	4DY2	9EA3	4EA2-E	6EA2-E	6EB2-M
6EA2-M	2DY2	9EA3	4EA2-M	6EA2-M	8EB2-E
4EA2-E	9DY3	6EA2-E	6EA2-E	6EA2-M	8EB2-M
4EA2-E	9DY2	6EA2-E	6EA2-M	6EA2-M	6EB2-E
4EA3-E	9DY3	6EA2-M	6EA2-M	6EA2-M	6EB2-M
4EA3-E	9DY2	6EA2-E	4EA2-E	4EA2-E	8EB2-E
4EA3-E	6DY3	6EA2-E	4EA2-M	4EA2-E	8EB2-M
4EA3-E	6DY2	6EA2-M	4EA2-E	4EA3-E	8EB2-E
4EA3-E	4DY2	6EA2-M	4EA2-M	4EA3-E	8EB2-M
4EA3-E	2DY2	4EA2-E	4EA2-E	4EA2-E	6EB2-E
4EA2-E	6DY3	4EA3-E	6EA2-E	4EA2-E	6EB2-M
4EA2-E	6DY2	4EA3-E	6EA2-M	4EA3-E	6EB2-E
4EA2-E	4DY2	4EA3-E	4EA2-E	4EA3-E	6EB2-M
4EA2-E	2DY2	4EA3-E	4EA2-M	4EA2-M	8EB2-E
4EA2-M	9DY3	4EA2-E	4EA2-M		

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**Compatible CIsCompatible CIsCompatible CIs

4EA2-M 8EB2-M  
 4EA2-M 6EB2-E  
 4EA2-M 6EB2-M

6EA2-E 2LA2  
 6EA2-M 2LA2

6EA2-E 2LB2  
 6EA2-M 2LB2

6EA2-E 2LC2  
 6EA2-M 2LC2

6EA2-E 2LO3  
 6EA2-M 2LO3

6EA2-E 6LS2  
 6EA2-M 6LS2  
 6EA2-E 4LS2  
 6EA2-M 4LS2  
 6EA2-E 2LS2  
 6EA2-M 2LS2  
 6EA2-E 2LS3  
 6EA2-M 2LS3

6EA2-E 4RV2-T  
 6EA2-M 4RV2-T  
 6EA2-E 2RV2-T  
 6EA2-M 2RV2-T

9EA3 43F2  
 9EA2 4SF2  
 6EA2-E 4SF3  
 6EA2-M 4SF3  
 6EA2-E 4SF2  
 6EA2-M 4SF2  
 4EA3-E 4SF2  
 4EA2-E 4SF2  
 4EA2-M 4SF2

8EB2-E 4AC2  
 8EB2-M 4AC2  
 8EB2-E 2AC2  
 8EB2-M 2AC2

8EB2-E 9DY3  
 8EB2-E 9DY2  
 8EB2-E 6DY3  
 8EB2-E 6DY2  
 8EB2-E 4DY2  
 8EB2-E 2DY2  
 8EB2-M 9DY3  
 8EB2-M 9DY2  
 8EB2-M 6DY3  
 8EB2-M 6DY2  
 8EB2-M 4DY2  
 8EB2-M 2DY2  
 6EB2-E 9DY2  
 6EB2-E 9DY3

6EB3-E 9DY2  
 6EB3-E 9DY3  
 6EB2-E 6DY2  
 6EB3-E 6DY2  
 6EB2-E 6DY3  
 6EB3-E 6DY3  
 6EB2-E 4DY2  
 6EB3-E 2DY2  
 6EB3-E 4DY2  
 6EB2-M 9DY2  
 6EB2-M 9DY3  
 6EB2-M 6DY2  
 6EB2-M 6DY3  
 6EB2-M 4DY2  
 6EB2-E 2DY2  
 6EB2-M 2DY2

6EB3-E 9EA2  
 6EB3-E 9EA3  
 6EB3-E 6EA2-E  
 6EB3-E 6EA2-M  
 6EB3-E 4EA2-E  
 6EB3-E 4EA2-M

8EB2-E 8EB2-E  
 8EB2-E 8EB2-M  
 8EB2-M 8EB2-M  
 8EB2-E 6EB2-E  
 8EB2-E 6EB2-M

## ACCESS SERVICE

9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)Channel Interface and Network Channel Codes (Cont'd)

## 9.3

Compatible Channel Interfaces (Cont'd)

## 9.3.5

Voice Grade (Cont'd)

(C)

Compatible CIsCompatible CIsCompatible CIs

8EB2-M	6EB2-E	8EB2-E	4RV2-T	8EC2	8EB2-M
8EB2-M	6EB2-M	8EB2-M	4RV2-T	8EC2	6EB2-E
6EB2-E	6EB2-E	8EB2-E	2RV2-T	8EC2	6EB2-M
6EB2-E	6EB2-M	8EB2-M	2RV2-T		
6EB3-E	8EB2-E			8EC2	4SF2
6EB3-E	8EB2-M	8EB2-E	4SF2	6EX2-B	2GO3
6EB2-M	6EB2-M	8EB2-M	4SF2	6EX2-A	6GS2
		8EB2-E	4SF3	6EX2-A	4GS2
8EB2-E	2LA2	8EB2-M	4SF3	6EX2-A	2GS2
8EB2-M	2LA2	6EB3-E	4SF2	6EX2-A	2GS3
		6EB2-E	4SF2		
8EB2-E	2LB2	6EB2-M	4SF2	6EX2-B	2LA2
8EB2-M	2LB2				
		8EC2	9DY2	6EX2-B	2LB2
8EB2-E	2LC2	8EC2	9DY3		
8EB2-M	2LC2	8EC2	6DY2	6EX2-B	2LC2
		84C2	6DY3		
8EB2-E	2LO3	8EC2	4DY2	6EX2-B	2LO2
8EB2-M	2LO3	8EC2	2DY2	6EX2-B	2LO3
8EB2-E	6LS2	8EC2	9EA2	6EX2-B	4LR2
8EB2-M	6LS2	8EC2	9EA3	6EX2-B	2LR2
8EB2-E	4LS2	8EC2	6EA2-E		
8EB2-M	4LS2	8EC2	6EA2-M	6EX2-A	6LS2
8EB2-E	2LS2	8EC2	4EA2-E	6EX2-A	4LS2
8EB2-M	2LS2	8EC2	4EA2-M	6EX2-A	2LS2
8EB2-E	2LS3			6EX2-A	2LS3
8EB2-M	2LS3	8EC2	8EB2-E		

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**

<u>Compatible CIs</u>		<u>Compatible CIs</u>		<u>Compatible CIs</u>	
6EX2-A	4SF2	6LO2	6LS2	4LR2	4SF2
6EX2-B	4SF2	6LO2	4LS2	4LR3	4SF2
		6LO2	2LS2		
6GO2	6GS2	6LO2	2LS3	6LS2	2LA2
6GO2	4GS2	4LO2	6LS2	4LS2	2LA2
6GO2	2GS2	4LO2	4LS2	4LS3	2LA2
6GO2	2GS3	4LO3	6LS2	2LS2	2LA2
4GO2	6GS2	4LO3	4LS2	2LS3	2LA2
4GO3	6GS2	4LO3	2LS3		
4GO2	4GS2	4LO3	2LS2	6LS2	2LB2
4GO3	4GS2	4LO2	2LS2	4LS2	2LB2
4GO2	2GS2	4LO2	2LS3	4LS3	2LB2
4GO2	2GS3	2LO3	2LS3	2LS2	2LB2
4GO3	2GS2	2LO3	2LS2	2LS3	2LB2
4GO3	2GS3	2LO2	2LS2		
2GO2	2GS2	2LO2	2LS3	6LS2	2LC2
2GO3	2GS2			4LS2	2LC2
2GO2	2GS3	6LO2	4SF2	4LS3	2LC2
2GO3	2GS3	4LO2	4SF2	2LS2	2LC2
		4LO3	4SF2	2LS3	2LC2
6GO2	4SF2				
4GO2	4SF2	4LR2	4LR1	6LS2	2LO3
4GO3	4SF2	4LR3	2LR2	6LS2	2LO2
		4LR2	4LR2	4LS2	2LO2
6GS2	2GO2	4LR2	2LR2	4LS2	2LO3
4GS2	2GO2	2LR2	2LR2	4LS3	2LO2
4GS3	2GO2	2LR3	2LR2	4LS3	2LO3
4GS2	2GO3				

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(C) Voice Grade (Cont'd)**Compatible CIsCompatible CIsCompatible CIs

6LS2	4SF2	4SF3	9DY2	4SF3	2LA2
4LS3	4SF2	4SF2	9DY3		
		4SF3	6DY3	4SF2	2LB2
4NO2	6DA2	4SF2	6DY3	4SF3	2LB2
4NO2	4DA2	4SF2	6DY3		
4NO2	2DA2	4SF3	6DY2	4SF2	2LC2
2NO2	2DA2	4SF2	4DY2	4SF3	2LC2
		4SF3	4DY2		
4NO2	4DE2	4SF3	2DY2	4SF2	2LO3
4NO2	2DE2	4SF2	2DY2	4SF3	2LO3
4NO2	4NO2	4SF3	9EA2	4SF2	2LR2
4NO2	2NO2	4SF3	9EA3	4SF3	4LR2
2NO2	2NO2	4SF3	4EA2-E	4SF3	2LR2
2NO3	2NO2	4SF3	4EA2-M		
				4SF3	6LS2
2NO3	2PR2	4SF3	6EB2-E	4SF2	4LS2
		4SF3	6EB2-M	4SF3	4LS2
4RV2-0	4RV2-T	4SF3	2GO3	4SF2	2LS2
4RV2-0	2RV2-T	4SF3	6GS2	4SF2	2LS3
4RV2-0	2RV2-T	4SF2	6GS2	4SF3	2LS2
		4SF2	6GS2	4SF3	2LS3
4RV2-0	4SF2	4SF3	4GS2		
		4SF2	2GS2	4SF3	4RV2-T
4SF2	4AC2	4SF2	2GS3	4SF2	4RV2-T
4SF2	2AC2	4SF3	2GS2	4SF2	2RV2-T
		4SF3	2GS3	4SF3	2RV2-T
4SF3	9DY3				
4SF2	9DY2	4SF2	2LA2	4SF3	4SF3

---

**ACCESS SERVICE**

---

**9.        Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3       Channel Interface and Network Channel Codes (Cont'd)****9.3.5    Compatible Channel Interfaces (Cont'd)****(C)       Voice Grade (Cont'd)****Compatible CIs**

4SF3	4SF2
4SF2	4SF2

4TF2	4TF2
4TF2	2TF2
2TF3	2TF2

## ACCESS SERVICE

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(D) Program Audio**Compatible CIs

4AH5-B 2PG1-3  
 4AH5-B 2PG1-5  
 4AH5-B 2PG1-8  
 4AH5-B 2PG2-3  
 4AH5-B 2PG2-5  
 4AH5-B 2PG2-8  
 4AH6-C 2PG1-3  
 4AH6-C 2PG1-5  
 4AH6-C 2PG1-8  
 4AH6-C 2PG2-3  
 8AH6-C 2PG2-5

Compatible CIs

4AH6-D 2PG1-3  
 4AH6-D 2PG1-5  
 4AH6-D 2PG1-8  
 4AH6-D 2PG2-3  
 4AH6-D 2PG2-5  
 4AH6-D 2PG2-8  
 4DS8-15E 2PG1-3  
 4DS8-15F 2PG1-5  
 4DS8-15G 2PG1-8  
 4DS8-15H 2PG1-1  
 4DS8-15E 2PG2-3

Compatible CIs

4DS8-15F 2PG2-5  
 4DS8-15G 2PG2-8  
 4DS8-15H 2PG2-1  
 2PG2-1 2PG1-1  
 2PG2-1 2PG2-1  
 2PG2-3 2PG1-3  
 2PG2-3 2PG2-3  
 2PG2-5 2PG1-5  
 2PG2-5 2PG2-5  
 2PG2-8 2PG1-8  
 2PG2-8 2PG2-8

**(E) Video Digital Transport ServiceTV-1 Analog**Compatible CIs

02TV7.15	02TV7.15
04TV6.15	04TV6.15
	04TV6.15A
04TV6.15A	04TV6.15A
	04TV6.15
04TV6.20A	04TV6.20A
	04TV6.20
04TV7.15	04TV7.15
04TV7.15A	04TV7.15A
04TV7.20A	04TV7.20A
06TV6.15	06TV6.15
	06TV6.15A
06TV6.15A	06TV6.15A
	06TV6.15
06TV6.20A	06TV6.20A
06TV7.15	06TV7.15
08TV6.15A	08TV6.15A
10TV6.15A	10TV6.15A
10TV6.20A	10TV6.20A

---

**ACCESS SERVICE**


---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(F) Wideband Analog**Compatible CIs

4AH5-B 4AH5-B  
 4AH6-C 4AH5-B  
 4AH6-C 4AH6-C

4AH6-D  
 4AH6-D  
 4AH6-C

Compatible CIs

4AH6-D 4AH6-D

4AH5-B 4AH5-B  
 4AH6-C 4AH5-B  
 4DU8-A,B, or C  
 4AH6-D 4DU8-A,B, or C

Compatible CIs

4WD5-I 4WA5-1  
 4WD5-2 4WA5-I  
 4WD5-3 4WA5-2

4DS8-15  
 4DU8-A,B, or C

**(G) Wideband Data**Compatible CIs

8WB5-18S 12WC6-18  
 8WB5-19A 10WC6-19  
 8WB5-19S 12WC6-19

Compatible CIs

8WB5-23A 10WC6-23  
 8WB5-23S 12W6-23S  
 8WB5-40S 12W6-40

Compatible CIs

8WB5-50A 10WC6-50  
 8WB5-50S 12WB6-50

## ACCESS SERVICE

9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)Channel Interface and Network Channel Codes (Cont'd)

## 9.3

Compatible Channel Interfaces (Cont'd)

## 9.3.5

Digital Data

(H)

Digital Data

(1)

Compatible CIsCompatible CIsCompatible CIs

			4DS8-15	6DU5-48	
4DS8-15	4DU8-15+	4DS8-15	6DU5-56	4DU5-96	4DU5-96
4DS8-15	4DU8-24	4DS8-15	6DU5-96	6DU5-24	6DU5-24
4DS8-15	4DU8-48	4DU5-24	4DU5-24	6DU5-48	6DU5-48
4DS8-15	4DU8-56	4DU5-48	4DU5-48	6DU5-56	6DU5-56
4DS8-15	6DU5-96	4DU8-56	4DU5-56	6DU5-96	6DU5-96
4DS8-15	6DU5-24	4DS9-15	4DU5-19	4DS6-44A	4DU5-19
4DS9-15B	4DU5-64	4DS6-44A	4DU5-64		

Available only as a cross connect of two digital circuits at appropriate digital speeds at a Telephone Company hub.

+

---

**ACCESS SERVICE**


---

**9. Interface Groups, Transmission Specifications and Channel Codes (Cont'd)****9.3 Channel Interface and Network Channel Codes (Cont'd)****9.3.5 Compatible Channel Interfaces (Cont'd)****(I) High Capacity**Compatible CIsCompatible CIs

4DSO-63	4DSO-63		4DS8-15	4DU8-8
4DSO-63	6DU8-A,B or C	4DS8-15J	4DS8-15J	6DU8-A
4DSO-63	4DU8-A,B or C	4DS8-15K	4DU8-A	
4DS6-27	4DS6-27		6DU8-B	
4DS6-27	6DU8-A,B or C	4DS8-15K	4DS8-15K	4DU8-B
4DS6-27	4DU8-A,B or C	4DS8-15K	6DU8-C	
4DS6-44	4DS6-44		4D78-C	
4DS6-44	6DU8-A,B or C	4DS9-31	4DS9-31	4DS9-31
4DS6-44	4DU8-A,B or C	4DS9-4DU8-A,B or C	6DU8-A,B or C	
4DS8-15	4DS8-15+		4DU9-A,B or C	4DU8-A,B or C
4DS8-15	6DU8-B		4DS9-15	4DU5-19
4DS6-44A	4DU5-19		4DS9-15B	4DU5-64
4DS6-44A	4DU5-64			

Available only as a cross connect of two individual circuits of 1.544 Mbps facilities at a Telephone Company hub.

+